

## MQ Power WhisperWatt 25 kVA to 150 kVA – Single / Three Phase

MODEL	DCA25SSI	DCA45SSI	DCA70SSI	DCA85SSJ*	DCA125SSI	DCA150SSJ	DCA150SSI
<b>Generator</b>							
Design	Revolving field, Self-Ventilated, Drip-Proof, Single Bearing						
No. of poles	4-pole						
Excitation	Brushless with AVR						
Standby rating	22 kW (27.5kVA)	40 kW (50kVA)	62 kW (77kVA)	75 kW (94kVA)	110 kW (137kVA)	132 kW (165kVA)	132 kW (165kVA)
Prime rating	20 kW (25kVA)	36 kW (45kVA)	56 kW (70kVA)	68 kW (85kVA)	100 kW (125kVA)	120 kW (150kVA)	120 kW (150kVA)
Generator RPM	1800						
Voltage - 3 phase	208, 220, 240, 416, 440, 460, 480V Switchable						
Voltage - 1 phase	120, 127, 139, 240, 254, 277V Switchable						
Armature connection	Star with Neutral / Zigzag						
Voltage regulation (no load to full load)	±0.5%						
Frequency	60 Hz						
Frequency regulation (steady state load)	±0.25% Optional Electronic Governor +0.25%	±0.25% Includes Electronic Governor	±0.25% Includes Electronic Governor	±0.25% Includes Electronic Governor	±0.25% Includes Electronic Governor	±0.25% Includes Electronic Governor	±0.25% Includes Electronic Governor
Power factor	0.8						
Sound level dB(A) Full load at 23 feet	63	65	68	68	68	68	69
<b>Diesel Engine</b>							
Make / Model	Isuzu BV-4LE2	Isuzu BU-4JJ1T	Isuzu BJ-4JJ1X	John Deere 4045HF285	Isuzu 4HK1X	John Deere 6068HF285	Isuzu 6HK1X
Emissions	Interim Tier 4	Interim Tier 4	Tier 3	Tier 3	Tier 3	Tier 3	Tier 3
Starting system	Electric						
Design	4-cycle Water cooled Direct injection	4-cycle Water cooled Direct injection Turbocharged	4-cycle Water cooled Direct injection Turbocharged Charge Air Cooled	4-cycle Water cooled Direct injection Turbocharged Charge Air Cooled	4-cycle Water cooled Direct injection Turbocharged Charge Air Cooled	4-cycle Water cooled Direct injection Turbocharged Charge Air Cooled	4-cycle Water cooled Direct injection Turbocharged Charge Air Cooled
Displacement	2179 cc	2999 cc	2999 cc	4500 cc	5193 cc	6800 cc	7790 cc
No. of cylinders	4	4	4	4	4	6	6
Bore x Stroke (mm)	85 x 96	95.4 x 104.9	95.4 x 104.9	106 x 127	115 x 125	106 x 127	115 x 125
Gross HP	34.3	67.1	97.9	126	173	197	240.1
Fuel tank capacity gal.(liters)	17 (65)	26 (100)	40 (150)	40 (150)	63 (240)	69 (260)	74 (280)
Fuel consumption full load gph (lph) 3/4 load gph (lph) 1/2 load gph (lph) 1/4 load gph (lph)	1.66 (6.3) 1.21 (4.6) 0.85 (3.2) 0.58 (2.2)	2.8 (10.6) 2.1 (8.0) 1.5 (5.6) 0.9 (3.4)	4.1 (15.4) 3.1 (11.9) 2.2 (8.4) 1.4 (5.2)	5.3 (20.2) 4.4 (16.6) 3.3 (12.4) 2.0 (7.5)	7.3 (27.6) 5.7 (21.7) 4.1 (15.4) 2.5 (9.5)	9.0 (33.9) 7.1 (26.9) 5.2 (19.7) 3.0 (11.5)	8.9 (33.6) 7.5 (28.3) 5.0 (19.0) 3.1 (11.9)
Coolant capacity gal. (liters)	1.74 (6.6)	2.96 (11.2)	3.09 (11.7)	3.91 (14.8)	5.33 (20.2)	4.6 (17.5)	7.8 (29.5)
Oil capacity gal. (liters)	2.25 (8.5)	3.96 (15.0)	3.96 (15.0)	3.88 (14.7)	6.1 (23.0)	8.19 (31.0)	10.6 (40.0)
Battery	12V 53Ah x 1	12V 72Ah x 1	12V 72Ah x 1	12V 72Ah x 1	12V 128Ah x 1	12V 128Ah x 1	12V 100Ah x 2 24V system
<b>Size</b>							
LxWxH in. (cm)	73 x 30 x 39 (185 x 75 x 100)	76 x 35 x 49 (194 x 90 x 125)	94 x 35 x 55 (240 x 90 x 140)	102 x 35 x 55 (260 x 90 x 140)	120 x 44 x 56 (305 x 110 x 140)	126 x 48 x 59 (320 x 120 x 150)	134 x 48 x 59 (340 x 120 x 150)
Approx Net Wt lbs. (kg)	1411 (640)	2282 (1035)	2755 (1250)	3547 (1609)	4700 (2131)	5313 (2410)	5899 (2675)
<b>Amps</b>							
Single phase 120V	55.6A (4 wire) 60A x 2 (zigzag)	100A (4 wire) 108A x 2 (zigzag)	155.5A (4 wire) 168A x 2 (zigzag)	188.9A (4 wire) 250A x 2 (zigzag)	277.8A (4 wire) 301A x 2 (zigzag)	333.3A (4 wire) 361A x 2 (zigzag)	333.3A (4 wire) 361A x 2 (zigzag)
Single phase 240V	27.8A (4 wire) 60A (zigzag)	50A (4 wire) 108A (zigzag)	77.8A (4 wire) 168A (zigzag)	94.4A (4 wire) 250A (zigzag)	138.9 (4 wire) 301A (zigzag)	166.7A (4 wire) 361A (zigzag)	166.7A (4 wire) 361A (zigzag)
Three phase 240V	60A	108A	168A	204A	301A	361A	361A
Three phase 480V	30A	54A	84A	102A	150A	180A	180A

\*Specially designed for high single phase output



Your MQ Power dealer is:

Cessco Inc.  
4222 NE Columbia Blvd.  
Portland, OR 97218



Toll Free: 1-800-882-4959